

Bulletin 1494F Fixed-Depth Flange-Mounted Disconnect Switches

Disconnect Switches




Choose a disconnect switch catalog number plus any additional accessories from the fuse clip kit and fuse block adapter plate kit tables.

Disconnect Switches for Type 1, 3R, and 12 Enclosures												
Continuous Current Rating [A] 600V AC 250V DC	UL and CSA Applications Maximum Hp				AC 1-Phase			DC*	IEC Applications Maximum kW (AC23)			Fusible or Non-Fusible Switch
	3-Phase, 60 Hz				115V	230V	250V		3-Phase, 50 Hz			
	200... 208V	230V	460V	575V				220... 240V	380... 440V	500... 600V	Cat. No.	
30	7.5	7.5	15	20	2	3	5	5.5	11	15	1494F-N30	
60	15	15	30	50	3	10	10	11	22	30	1494F-N60	
100	25	30	60	75	—	15	20	22	45	55	1494F-N100	
200	50...60	60	125	150	—	—	40	45	75	75	1494F-N200	

* Ratings based on utilizing two poles in series to break one line of the DC supply voltage and the remaining pole breaking the second DC supply line.

Fuse Clip Kit and Fuse Block Adapter Plate Kit

Select both a fuse clip kit **and** a fuse block adapter plate.

Switch Rating [A]	Fuse Clip Rating [A]							
		Fuse Clip Kit						Fuse Block Adapter Plate Kit
		Class R		Class J	Class H			
		250V	600V	250/600V	250V	600V		
Cat. No.		Cat. No.	Cat. No.	Cat. No.	Cat. No.	Cat. No.		
30	30	1401-N50	1401-N51	1401-N42	1401-N41	1401-N42	1494F-F30	
	60	1401-N51	1401-N52	1401-N43	1401-N42	1401-N43	1494F-F60	
60	30	1401-N50	1401-N51	1401-N42	1401-N41	1401-N42		
	60	1401-N51	1401-N52	1401-N43	1401-N42	1401-N43		
	100	1401-N53	1401-N53	1401-N44	1401-N44	1401-N44		
100	60	1401-N51	1401-N52	1401-N43	1401-N42	1401-N43	1494F-F100	
	100	1401-N53	1401-N53	1401-N44	1401-N44	1401-N44		
	200	1401-N54	1401-N54	1401-N45	1401-N45	1401-N45		
200	100	1401-N53	1401-N53	1401-N44	1401-N44	1401-N44	1494F-F200	
	200	1401-N54	1401-N54	1401-N45	1401-N45	1401-N45		
	400	—	—	1401-N171	—	—		